




i-GATE

Gate opener with IOS & Android Apps.

	I-GATE-PRIME	I-GATE-PLUS	I-GATE-WIFI
Connection.	Cellular	Cellular	IP
Numbers for caller ID access.	250	1280	N/A
FOTA – Upgrade firmware via SMS.	✓	✓	✗
Automatic firmware upgrade via WEB.	✗	✗	✓
Trigger, latch and unlatch gates by SMS or with app.	✓	✓	✓
Auto call feature to schedule outgoing call (prevents SIM card being deactivated).	✓	✓	N/A
Activity log feature.	✓	✓	✗
Includes 7 day time clock.	✓	✓	✗
Check stored numbers by SMS.	✓	✓	N/A
Volt free momentary relay outputs.	2	1	1
Check if gates are opened or closed (limit switch).	✓	✗	✗
Check relay status.	✓	✓	✓
SMS passcode access for non stored numbers.	✓	✓	N/A
Store up to four phone numbers to receive SMS alerts each time the unit is used to grant access.	✓	✓	N/A
Program times for the relay(s) to operate automatically.	✓	✓	N/A
Push-To-Exit time limits.	✓	✓	✗
E-LOOP* Connection Features.	✗	✓	✗
SMS Notification when e-LOOP battery is low (4 Numbers).	✗	✓	✗
e-LOOP only OR e-LOOP & remote lock out times.	✗	✓	✗
Suspend times.	✗	✓	✗
Voice control via alexa/Google integration.	✗	✗	✓
Share with other users.	✗	✗	✓
Permission levels.	✗	✗	✓

*e-Loop sold separately.
*Full app functionality will be released at a later date. Direct SMS commands can be used.



DETAILS - PRIME & PLUS	
Power	12-24v ac/dc (not supplied).
Current	25mA (standby). 80mA (when called).
Weather Rating	IP67
Relay Load	24v 2A
Relay Type	N/C and N/O. Latching & Momentary.

DETAILS - WIFI	
Working Frequency	Wi-Fi (b/g/n) 2,4GHz
Power	8-36VAC/DC (not supplied)
Current	27mA (Standby). 50mA (In operation).
Weather Rating	Outdoor unit: IP67 Din rail unit: IP20
Relay Load	3A
Relay Type	N/C and N/O. Latching & momentary